

GB 15k Series

3 Channels GAS Mixer



Each Channel: 0 – 15000 mL/min

Accuracy: 2.0%

Repeatability: 0,20% of reading

Response time: 1 s

Software bundle.

For INDUSTRIAL Flows

Total Mixture Flow Rate: Up to 45 L/min



Up to 3 Channels.

GB 15k can manage and mix up to 3 different sources of gas with incredible high precision, creating accurate gas mixtures.

Touch Screen.

Our Touch Display allows you to manage and control any value and parameter of your flows in real time and without effort.

Compatible.

The integrability with ProfiBus, ModBus, & Matlab Simulink gives the possibility of an easy integration into other systems.


Accurate. Compact. Reliable.

“Gas Blender 15K Series is an innovative all-in-one replacement for traditional mass flow controllers multi-channel solutions. Our device allows up to 3 channel gas mixing processes, all in a single box ready for a rack mount.

All parameters could be controlled by the Resistive Touch Panel specifically designed for industrial applications.”

Specifications.


Accuracy: (for each channel)	N2, 20 °C, 101.325 kPa (1 atm): 0,1-100% / FS: 1% of setpoint
Repeatability:	0,20% of reading
Response time: (for each channel)	1000 ms
Power Supply:	In Bundle
Operation Pressure:	Max 5 bar
Working Temperature:	0-50 °C
Mass Flow Rates: (for each channel)	0 – 15000 mL/min (standard)
Total Mixture Flow Rate:	Up to 45 L/min
Gases:	N2, O2, CO2, CH4, Air, He, H2 (additional gases supported on request)
Compatibility:	Profibus, Modbus, Matlab Simulink
Communication:	RS485 with open proprietary protocol
Fittings:	Depends from the applications.
Inlet Gas Channel:	3 Inputs
Outlet Gas Channel:	1 Output of mixed gases
User Interface:	Resistive Touch Display.
Certifications:	CE, Made in Italy



Industrial Rack.
Industrial rack mount box ready.
Easy assembly routine and integration for any industrial application.



Touch Screen
The Resistive Touch Display allows you to control the parameters via the screen with latex or work gloves.



3 Channels.
You can customize the number of channels you will need for your solutions.

